

LumaGlow Patio Planter Light

3000K-LumaGlow-20in

The Environmental Lights LumaGlow Patio Planter Light is a great way to add decorative lighting to your potted plants. Position this light in your garden or patio area to add charm and lighting effects. The LumaGlow Patio Planter Light plugs directly into a standard wall outlet and features a built-in controller to adjust brightness and a 24 hour timer to automatically turns your light on and off every day.

PRODUCT REFERENCE GUIDE

- High output for a dramatic effect at full brightness
- Four selectable brightness options to suite any environment
- Diffused LED covering for even and dot-free appearance
- Built-in 24hr timer with four duration options
- Fully sealed to keep water off the floor for indoor applications.
- Easy knock-out drainage hole for outdoor applications
- Weather resistant to IP65 standards – suitable for outdoor use, avoid submersion.

Ideal Application: Uplighting for indoor or outdoor potted plants

TECHNICAL SPECIFICATIONS

Product	3000K-LumaGlow-20in
Input Voltage	120VAC
Input Current	0.65A (maximum)
CCT	3000K
Timer Settings	4, 6, 8, 12 and 24-hour on timer
Brightness Settings	4 brightness options
Inner Diameter	18 in
Outer Diameter	20.75 in
Rating	UL, IP65
Warranty	1 year



SETUP

1. To begin using, simply insert the plug into a standard 120VAC wall outlet. The LumaGlow light will default to full brightness and reset the timer function each time the LumaGlow ring is connected to power. See the 'Timer' section below for more information about the internal timer.
2. If drainage through the bottom of the ring is desired, use a screwdriver and hammer (or similar tools) to punch out the small circle in the middle to the light.

PROGRAMMING

A BRIGHTNESS

Use the arrow buttons under the brightness setting to adjust the brightness from 1 to 4 (Level 4 being the brightest setting).



B TIMER

The timer function has 5 settings. The default setting is timer-off, indicated by all 4 LEDs being off.

Pressing the arrow keys will illuminate and cycle through the LEDs under 4, 6, 8 and 12 hours indicated by the numbers marked on the key. For example, the '6' setting means that the light will stay on for 6 hours and then shut off. The next day it will come back on for another 6 hours, starting 24hrs from when the timer setting was selected.



Hold the power key for 5 seconds to set the timer start time. The timer will start the "on" time after the LEDs blink and will come back on at this time every day.

C POWER KEY

Pressing the power key once will turn the LumaGlow light on and off.

Using the power key to turn the light off during the on time, the light will resume normal function the next day.

The power button can be used to reset the timer start time. Hold the button down for 5 seconds and the timer LEDs will blink to indicate that the new start time has been selected.



For More Information

888.880.1880

ContactUs@EnvironmentalLights.com

© 2021, Environmental Lights. All rights reserved.