

StudioPro Digital 6 Channel Controller



Studio Ready, 6-Channel LED Controller

The StudioPro Digital 6 Channel LED Controller is an easy-to-program LED controller for use with up to six channels of LED lighting. Power-off memory saves the specific values for each channel. This reduces configuration time and allows for a set-and-forget set-up. Equipped with six channels of output, you can utilize our 6-in-1 ColorPlus 5050 LED Strip Light or control up to six individual single-color LED strip light reels.

- Six-channel LED controller
- Four amps per channel
- Power-off memory
- 20kHz PWM output

StudioPro Digital 6 Channel LED Controller

Specifications

Output	StudioPro Digital 6 Channel LED Controller
	6-Digi-Display
Electrical	
Input Voltage (DC)	12 or 24
Power (W)	288 or 576
Output Channels	6
Output Current	24000
Output Voltage (DC)	12 or 24
Warranty	1 year
PWM Frequency (Hz)	23,000
Physical	
Finish	White
Length (m)	176
Width (mm)	46.5
Height (mm)	31
Rating	CE, RoHS,FCC

