

StudioPro DMX Digital Decoder



5 Channel Decoder With Digital Display

This decoder is highly configurable and features a convenient digital display. The display allows the setup of DMX addresses without the use of DIP switches. It can also change the PWM frequency and dimming curve to suit your project's specific needs. This decoder features a standalone mode, which allows it to function without the need for any additional software. Additionally, the standalone mode can be used to set the decoder as a master controller when paired with other decoders.

- 5 channels
- 8 amps per channel maximum sustained power
- 12 or 24 VDC input and output
- Digital readout legibly displays the DMX address, which is useful in dimly lit rooms
- Easily change DMX address without DIP switch math
- Converts standard DMX signal to PWM output suitable for driving 12 or 24 VDC LED lighting
- Standalone mode – no software required



DMX Digital Decoder

Specifications

StudioPro 5 Channel DMX Digital Decoder - 8A per Channel

DMX-5-8A

Power (W)	480 or 960
Finish	Black
Length (mm)	164
Width (mm)	74
Height (mm)	39
Warranty	1 year
Voltage (DC)	12 or 24
Input Current (mA)	40,500
Rating	UL Recognized, CE, RoHS, FCC

