

Single Channel StudioPro LED Dimmer



High-Capacity Single Channel LED Dimmer

The Single Channel StudioPro LED Dimmer is a simple yet powerful high-capacity LED dimmer. With a single knob on the top of the unit, you can dim up to 20 amps of LEDs from 100% brightness to fully off to achieve the perfect lighting for any installation. The design utilizes a 5kHz PWM frequency to ensure no visible flicker on camera. The Single Channel StudioPro LED Dimmer features dimming to achieve the exact look that is needed on set, stage or anywhere where precise lighting control matters. With a 20 Amp capacity, the entire load of a large installation can be placed on one dimmer, to ensure even and balanced lighting.

- 20 amp capacity
- 5Khz PWM frequency
- Fully dimmable from 100% to 0% brightness
- Dimmer knob clicks when fully off
- Control up to 240 Watts @ 12 VDC or 480 Watts @ 24 VDC
- PHX terminals
- Mounting holes on bottom



Single Channel StudioPro LED Dimmer

Specifications

Single Channel Studio Pro LED Dimmer	
pro-dim-5000-20a	
Physical	
Outputs	2
Mounting Options	Mounting holes on bottom
Mounting Hole Diameter	3mm
Finish	White
Height (mm)	50
Length (mm)	150
Width (mm)	46
Warranty	3 years
Electrical	
Input Voltage (VDC)	12 or 24
Max Current (A)	20
Max Power @ 12VDC (W)	240
Max Power @ 24VDC (W)	480
Output Frequency (Hz)	5,000

